



## T12 IP67 Pig Farm LED Light Fitting



### Description

- The tube is certificated by SAA, CE, ROHS, IP67.
- Meet IEC VDE safety standard with built-in isolated driver.

Item	Material	Description
PC pipe	Full PC Pipe	Safety for waterproof
	Pure PC / 94V-0	Will not Fade
		will not burst
		Anti-weak base
Connector	Nylon+NBR for seal	Alkali, wear resistance,
		Weather resistance
		CE, IP68 Level
Waterproof End Cap	PC+Fiber	Will not Fade
		Anti-weak base
PCB board	Aluminum	Hi-pot test up to 2000V
		1.5 transmission rate

LED driver designed_Traic dimmable		
Main Components	Brand	Specification
Electrolytic Capacitance	Aishi	50,000hrs lifetime
Dimmable IC	MPS	Dimm brightness from 0.5%-100%)
MOS	Silan	SV4N65 TO-220
Transformer	China	MAX wattage is 36W

Item	Material	Description
LED chips SMD2835	10*30mil	26-28lm/pcs
	CRI	Ra80+
	Gold wire	Heraeus gold
	Bracket	copper bracket.

### Product information

Product Code	Type of Driver	Type of Cable	Power	LED info	Total Length	Lumens	Remark
HT-T 12PIG1	180-264Vac @ Dimmable 100-265Vac @ Non-dimmable	0.5M	30W	SMD2835 168pcs	L: 1500mm OD32mm	3300Lm Max	IP 67
HT-T 12PIG2	180-264Vac @ Dimmable 100-265Vac @ Non-dimmable	1.5M	30W	SMD2835 168pcs	L: 1500mm OD32mm	3300Lm Max	IP 67

- This unit MUST be installed and wired by a qualified electrical contractor.
- Please cut the power off when install and remove the products to avoid risk of electric shock.
- Fixture control gear/AC cable MUST BE MOUNTED ABOVE any insulation covering and waterproof box.
- IK10 (20 Joules) protection against mechanical impact.
- 5,000K
- 3 year warranty

